П

TPS 840 Series Microminiature SMT Side Actuated







Features/Benefits

- 3.5 x 3.55 mm footprint
- Front PIP leads option for strong shear resistance
- ESD pin option
- Reduced footprint

Typical Applications

- Nomad devices
- Remote controls
- Personal health diagnostics
- Consumer electronics

Specifications

FUNCTION: momentary action
CONTACT ARRANGEMENT: 1 make contact = SPST N.O.
TERMINALS: G and front PIP types for SMT
TRAVEL: 0.2mm + 0.2mm / -0.1 mm

LIFE: 100,000 cycles

	Operating	SMT	
Type	Force (gf)	Leads	Pegs
Without ground pin	,		
TPS840 GM SMTR LFS	160 -40/+70	G leads	No
TPS840 GK SMTR LFS	220 -70/+80	G leads	No
TPS840 PM SMTR LFS	160 -40/+70	P leads	No
TPS840 PK SMTR LFS	220 -70/+80	P leads	No
TPS840 GMP SMTR LFS	160 -40/+70	G leads	Yes
TPS840 GKP SMTR LFS	220 -70/+80	G leads	Yes
With ground pin			
TPS840 ESDGM SMTR LFS	160 -40/+70	G leads	No
TPS840 ESDGK SMTR LFS	220 -70/+80	G leads	No
TPS840 ESDPM SMTR LFS	160 -40/+70	P leads	No
TPS840 ESDPK SMTR LFS	220 -70/+80	P leads	No
TPS840 ESDGMP SMTR LFS	160 -40/+70	G leads	Yes
TPS840 ESDGKP SMTR LFS	220 -70/+80	G leads	Yes

Electrical

Environmental

OPERATING TEMPERATURE: -40°C to 85°C

Process

SOLDERING: This component is suited to the following methods: Infrared Reflow Soldering in accordance with IEC61760-1

Packaging


In reels of 3,500 pieces
Dimensions of reels according to EIA 481B
External diameter 330 mm

NOTE: Specifications listed above are for switches with standard options. For information on specific and custom switches, consult Customer Service Center.

How To Order

Our easy build-a-switch concept allows you to mix and match options to create the switch you need. To order, select desired option from each category and place it in the appropriate box.


For any part number different from those listed above, please consult your local representative.




Design Recommendations

- "P" leads are recommended for applications where shear resistance is of importance
- When a precise alignment between application button and the switch is requested, version with pegs are the right choice to limit the possible floating of the switch during solderability.





P SMT Leads with ESD option





TPS 840 Series Microminiature SMT Side Actuated

TAPE & REEL

